

Product information OpenBAT-F - BAT-FUSW99AWW99B0599S999ZH09.00.5103

| lame | OpenBAT-F |
|---|---|
| | |
| | |
| | |
| | Prop. 2 |
| | |
| | |
| | |
| | Rugged wireless LAN access point and/or client for use in industrial environments. IP65/67 water and dust resistant, rugged metal housing deployment in the |
| | field. |
| Delivery informations | |
| Availability | available |
| Product description | |
| Description | Rugged wireless LAN access point and/or client for use in industrial environments. IP65/67 water and dust resistant, rugged metal housing deployment in the |
| lost time and quantity | field. M12 - LAN combo port: 10/100/1000BASE-TX, 1000BASE-SX/LX |
| Port type and quantity Radio protocol | |
| | IEEE802.11a/b/g/h/n WLAN interface as per IEEE802.11n, up to 450MBit/s gross bandwidth. BAT-FUSW99AWW99B0599S999ZH09.00.5103 |
| Drder No. | BAT-FUSW99AWW99B0599S9992H09.00.5103 |
| Supported Radio Standards | 1st WLAN interface as per IEEE802.11n |
| Aore Interfaces | The WEAK Include as per lellouz. The |
| thernet | M12 - LAN combo-port: 10/100/1000BASE-TX, 1000BASE-SX/LX |
| ower supply/signaling contact | 1 x terminal block, 2-pin; 1 x terminal block, 2-pin |
| 24 interface | Configuration interface (COM) AT modem connection For automatic P2P connections verified over V.24 (train carriage coupling) Serial gateway for WLAN or |
| | virtual COM interface via WLAN |
| JSB interface | 1 x M12 USB interface for connecting an ACA-USB-M12 |
| Radio technology | |
| Antenna connector | N socket, 3 x MiMo antenna connectors |
| lange | Depends on type of antenna, frequency range and data rate. Use the BAT-Planner for planning your wireless network. |
| requency band | Supports 2.4 GHz and 5 GHz: 2400 -2483.5 MHz (ISM) and 5170 -5850 MHz |
| Nodulation | 22M0F7D (DSSS/0FDM) at 2.4 GHz20M0G7D (0FDM) at 5 GHz |
| Encryption | IEEE 802.11i / WPA2 with passphrase or 802.1x and hardware-accelerated AES, closed network, WEP64, WEP128, WEP152, user authentication, 802.1x /E |
| | LEPS, WPA1/TKIP. Please refer to the HiLCOS data sheet for further information. |
| Power requirements | |
| Dperating voltage | Voltage Range 1: 24 VDC (19.2-32 VDC); Voltage Range 2: 24 VDC (19.2-32 VDC) |
| Current consumption | 12.95 W |
| Ambient conditions | 0.00 |
| Operating temperature | 0 °C 60 °C |
| lote | Temperature of the surrounding air. |
| Storage/transport temperature Relative humidity (non-condensing) | -40 °C 85 °C 10 % 95 % |
| ATBF | |
| rotective paint on PCB | 58 years (MIL-HDBK-217F) No |
| Acchanical construction | NU |
| imensions (W x H x D) | 311 mm x 219 mm x 75 mm |
| Nounting | Wall mounting |
| Protection class | IP65, IP67 |
| Approvals | |
| Safety of information technology equipment | EN 60950-1, |
| Radio | FCC; EN 301 489-1, EN 301 489-17 |
| cope of delivery and accessories | |
| cope of delivery | Device, Installation user manual, CD/DVD with manual, V1 sealing cap for optical connection, Terminal cable, 2 x Power supply plug, 2 x Dust protection cap |
| | power supply connection, 4 x M12 cap, Cover cap for N connector, 2 x 50 0hm terminators, 3 x 3-dBi dipole dual-band antennas. |





| Industrial Ethernet:Industrial Wireless LAN:Chassis:OpenBAT:OpenBAT-F | | |
|--|---|--|
| https://www.e-catalog.beldensolutions.com:443/link/57078-24455-49859-24497-202741-400055/en/BAT-FUSW99AWW99B0599S999ZH09.00.5103/uistate | | |
| Accessories to order separately | External antennas; external surge protection; cables 2 m, 5 m, 15 m. Some countries does not allow all Antennas. For more information please have a look into | |
| | the Hirschmann Antenna Guide; mast mount adapter | |

For more information please contact: **Hirschmann Automation and Control GmbH** Stuttgarter Strasse 45-51 72654 Neckartenzlingen Germany Phone: +49 7127/14-1809 E-Mail: inet-sales@belden.com

The information published in the websites has been compiled as carefully as possible. It is subject to alteration without notice in technical as well as in price-related/commercial respect. The complete information and data were available on user documentation. Mandatory information can only be obtained by a concrete query.

