# STI Exit Stopper®



## PRODUCT OVERVIEW

The Exit Stopper is a unique and highly effective way to alert you to any unauthorised exits or entries through emergency exit doors. It can also serve as an inexpensive security device and help prevent theft. It is available in red or green and can be mounted or installed on almost any type of door, including remote placement of the sounder. The highly visible 'STOP' sign discourages unauthorised use of emergency doors.

## HOW IT WORKS

If the protected door is opened, the electronic Exit Stopper emits an ear piercing alarm. When the door is closed, a number of reset options are available including an automatic function. A variety of alarm durations and setup features are available (see User Programmable Features chart overleaf). A key operated override facility will silence the alarm and allow authorised exits. The Exit Stopper is fitted with a 9V PP3 alkaline battery.

# KEY FEATURES

#### **General Information**

• Prevent unauthorised exits and entries through emergency exit doors.

 Three year guarantee against breakage of polycarbonate in normal use (one year on electromechanical and electronic components).

#### Design

Compact design (136mm diameter and 50mm deep).

#### Construction

· Virtually indestructible polycarbonate cover is UV stabilised.

#### Installation

 Highly versatile; can be mounted or installed on any type of door, including remote placement of sounder.

• Can be installed and protecting doors in minutes.

#### Electronics

- Powered by a 9V PP3 alkaline battery (included).
- Incorporates a 12/24 VDC connection.
- · 40 milliamp 9 VDC trigger output.

#### Options

· Variety of user programmable features.

 A key operated override facility will silence the alarm and allow authorised exits.

#### Remote Wireless Monitoring of Exit Doors

 You can now be alerted to any vandalism or authorised use of a fire exit door in the event of an emergency. Upon activation, the Exit Stopper (when fitted with an optional transmitter and sounder) will emit a localised alarm as well as triggering the 4-Channel (STI 34104) or 8-Channel Receiver (STI 34108), providing a visual and audible indication, remotely.





# STI Exit Stopper®

Dimensions and Technical Information

#### MODELS AVAILABLE

NIODLLO	,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,,
STI-6400	Exit Stopper
STI-6401	Exit Stopper with delay and automatic reset feature
STI-6402	Exit Stopper, suitable for a double door installation
STI-6405	Exit Stopper with momentary reset
STI-6406	Exit Stopper with dual access control
Accessories:	
STI-6400-RK	Remote installation kit
STI-6400-RS	Remote 95/105 dB sounder
STI-6400WIR	Wireless Exit Stopper
STI-6400WIR8	Wireless Exit Stopper with 8 channel receiver
STI-V6400WIR4	Wireless Exit Stopper with 4 channel voice receiver
STI-C023/A	Spare key
STI-L6400	Alarm warning emergency exit sign
Options	
COLOURS	For green, add -G
AVAILABLE	(e.g. STI-6400-G for Exit Stopper in green)

User Programmable Features	JP2	JP3	JP4	JP5	JP7
High Volume* (105 dB)	ON				
Low Volume (95 dB)	OFF				
Immediate Arming*					ON
15 Second Arming Delay					OFF
Immediate Activation*				OFF	
15 Second Activation Delay				ON	
30 Second Alarm Duration*		OFF	OFF		
180 Second Alarm Duration		OFF	ON		
Continuous Alarm Duration		ON	OFF		
Door Prop Mode (5 beeps)		ON	ON		

\* Factory settings

