

Tripp Lite
1111 West 35th Street
Chicago, IL 60609 USA
Telephone: +(773) 869 1234
E-mail: saleshelp@tripplite.com

Model #: SU6000RT4UHVHW

SmartOnline 6kVA On-Line Double-Conversion UPS, 4U Rack/Tower, 200-240V Hardwire output



Highlights

- 6kVA / 6000VA / 5400W on-line double-conversion UPS; 0.9 power factor
- 200/208/220/230/240V 50/60Hz output; Economy mode option
- 4U Rack/Tower compatible; Hot-swap power and battery modules
- USB, RS232 & EPO ports; SNMP/WEB and contact-closure card options
- Front panel LEDs with detailed LCD monitoring and control screen
- Expandable runtime with optional external battery packs
- Hardwire input (3 wire); Hardwire output

Description

Tripp Lite SU6000RT4UHVHW 6000VA / 6kVA / 5400 watt on-line, double-conversion UPS system offers complete power protection for critical server, network and telecommunications equipment in a single 4U rack/tower compatible housing. Full-time active power conditioning provides clean, continuous dual-conversion AC output free of voltage fluctuations, power interruptions and line noise. Fault-tolerant auto-bypass prevents unexpected service interruptions during UPS overload or internal fault conditions. Detachable back panel PDU with manual bypass switch supports hot-swappable whole UPS replacement with no interruption to connected equipment. Single all-in-one rack / tower housing installs in only 4 rack spaces (4U) with a maximum installed depth of only 20.7 in. / 52.6cm. Maintains full-time sine wave output within 2% of selectable 200/208/220/230/240V nominal during brownouts as low 100V and overvoltages as high as 300V. Expandable runtime is supported with optional BP192V12-3U external battery packs. Battery independent restart ensures automatic UPS power-up without user interaction after lengthy power outages, even when batteries areexpired and require replacement. Double-conversion operation converts raw input from AC to DC, then re-synthesizes output power back to perfect sine wave AC with enhanced protection from harmonic distortion, fast electrical impulses and other hard-to-solve power problems not addressed by other UPS types. Highly efficient operation in optional economy mode significantly reduces BTU heat output and operating energy costs. Network-grade AC surge and noise suppression. Supports detailed monitoring of equipment load levels, self-test data and utility power conditions via built-in RS-232 and USB interfaces. Optional SNMP/Web and contact-closure communications card accessories available. HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X. Included PowerAlert monitoring software packages include PowerAlert Networ

Features

- Tripp Lite SU6000RT4UHVHW 6000VA / 6kVA / 5400 watt on-line, double-conversion UPS system in a single 4U rack/tower compatible housing
- Full-time active power conditioning maintains clean, continuous dual-conversion AC output free of voltage fluctuations, power interruptions and line noise
- Fault tolerant electronic bypass maintains utility output during a variety of UPS fault conditions
- Detachable back panel PDU contains hardwire input and output connections, plus manual bypass switch to support hot-swappable whole UPS replacement with no interruption to connected equipment
- Hardwire input and output connections supported
- Included rail kit supports 4U 19 inch rackmount installation in 4 post racks
- Optional 2POSTRMKITHD supports installation in 2 post 19 inch racks (1 required for SU6000RT4UHVHW)
- Optional 2-9USTAND supports upright tower placement (1 required for SU6000RT4UHVHW)
- Maximum installed rack depth of only 20.7 in. / 52.6cm inches
- Maintains full-time sine wave output within 2% of selected 200/208/220/230/240V nominal in double conversion mode
- Corrects brownouts to 156V at full load (100V at 50% load or less)
- Corrects overvoltages to 290V at full load (300V at 90% load or less)
- Supports 50/60Hz operation for worldwide frequency compatibility

- Double-conversion operation offers full-time AC to DC, then DC to AC conversion to maintain perfectly regulated sine wave AC output with enhanced protection from harmonic distortion, fast electrical impulses and other hard-to-solve power problems not addressed by other UPS types
- High efficiency ECONOMY MODE operation significantly reduces BTU heat output and operating energy costs
- Network-grade AC surge and noise suppression
- Supports detailed monitoring of equipment load levels, self-test data and utility power conditions via built-in RS-232, USB and optional SNMP card slot interfaces
- UPS card slot supports one card-based network interface option (part # SNMPWEBCARD) or dry-contact monitoring accessory (part # RELAYIOCARD)
- Optional SNMPWEBCARD offers communications and control via secure remote web and network interfaces
- Optional RELAYIOCARD supports six configurable hard contact closure outputs for custom event notification
- Optional RELAYIOMINI interface module offers three configurable hard contact closure outputs for custom event notification (requires removal of USB interface module)
- HID-compliant USB interface enables integration with built-in power management and auto shutdown features of Windows and Mac OS X
- Includes Free PowerAlert monitoring software packages; PowerAlert LOCAL for desktops and small business networks, PowerAlert NSA (Network Shutdown Agent) for larger networks and PowerAlert NMS (Network Management System) for monitoring up to 250 SNMP-enabled UPS, PDU and other networking devices
- Front panel LEDs and LCD readout with scroll controls support front-panel visual monitoring of all major
- UPS functions with support for a variety of control options to support advanced UPS settings and configurations
- LED/LCD display panel rotates for viewing in rackmount or tower configurations
- Supports Emergency Power Off (EPO) via built-in interface
- Battery independent restart ensures automatic UPS power-up without userinteraction after lengthy power outages, even when batteries are expired and require replacement
- BP192V12-3U external battery packs are field replaceable and hot swappable
- Some external battery configurations require the use of Tripp Lite's External Battery Configuration Software (see manual)
- Frequency conversion mode enables conversion of 60Hz to 50Hz or 50Hz to 60Hz (no de-rating)

Specifications

OUTPUT					
Output Volt Amp Capacity (VA)	5000				
Output kVA capacity (kVA)	6.0				
Output Watt Capacity (watts)	5400				
Output kW capacity	5.4				
Output power factor	0.9				
Crest Factor	3:1				
Nominal Output Voltage(s) Supported	200V; 208V; 220V; 230V; 240V				
Frequency compatibility	50/60 Hz (auto-selectable)				
Frequency compatibility details	Output frequency matches input nominal on startup; Frequency conversion mode enables conversion of 60Hz to 50Hz or 50Hz to 60Hz (no de-rating)				
Output voltage regulation (line mode)	+/- 2%				
Output voltage regulation (Economy line mode)	+/- 10%				
Output voltage regulation (Battery mode)	+/- 2%				

Built-in UPS output receptacles	Hardwire				
Output receptacle details	Hardwire input and output connections are mounted on a detachable PDU backplate with bypass switch to enable hot-swappable power module replacement				
Output AC waveform (AC mode)	Pure Sine wave				
Output AC waveform (battery mode)	Pure Sine wave				
INPUT					
Rated input current (at maximum load)	31.9A (200V), 30.6A (208V), 29A (220V), 27.7A (230V), 26.6A (240V)				
Nominal Input Voltage(s) Supported	200V AC; 208V AC; 220V AC; 230V AC; 240V AC				
UPS input connection type	Hardwire				
Recommended Electrical Service	40A (200/208v); 30A (220/230/240v)				
BATTERY					
Full load runtime (minutes)	2 minutes (5400 watts)				
Half load runtime (minutes)	8.5 minutes (2700 watts)				
Expandable battery runtime	Runtime is expandable with external battery packs				
External battery pack compatibility	BP192V12-3U				
DC system voltage (VDC)	192				
Battery recharge rate (included batteries)	6 hours from 10% to 90% (internal batteries)				
Replacement battery cartridge (internal UPS battery replacement)	RBC5-192				
Battery Access	Front panel battery access door				
Battery replacement description	Hot-swappable, user replaceable internal batteries				
VOLTAGE REGULATION	N				
Voltage regulation description	Online, double-conversion power conditioning				
Overvoltage correction	Corrects overvoltages as high as 300V (
Undervoltage correction	Corrects undervoltages as low as 100 (
LEDS ALARMS & SWIT	CHES				
LED Indicators	6 LEDs indicate line power, online mode, economy/bypass mode, on-battery, charger and AC output status; LCD screen offers additional information and control options				
Alarms	Unique audible alarms for all major UPS, environmental and power conditions (see manual)				

Alarm cancel operation	Alarm cancel switch				
Switches	Includes main power off/on switch, plus 2 switches to set and execute scrollable LCD functions. A manual bypass switch featured on the detachable PDU allows for complete removal of the UPS during routine maintenance without disrupting power to connected loads				
SURGE / NOISE SUPPR	ESSION				
UPS AC suppression response time	Instantaneous				
EMI / RFI AC noise suppression	Yes				
PHYSICAL					
Installation form factors supported with optional accessories	2 post rackmount (2POSTRMKITHD); Tower (2-9USTAND)				
Primary form factor	Rackmount				
UPS / Power Module dimensions in primary form factor (height x width x depth / inches)	6.85 x 17.5 x 20.7				
UPS / Power Module dimensions in primary form factor (height x width x depth / cm)	17.4 x 44.5 x 52.6				
Installed whole system total rack space height (rack spaces)	4U				
Secondary form factor	Tower				
UPS / Power Module weight (lbs)	116.2				
UPS / Power Module weight (kg)	52.8				
UPS Shipping dimensions (height x width x depth / inches)	12.7 x 23.6 x 29.1				
UPS Shipping dimensions (height x width x depth / cm)	32.3 x 59.9 x 73.9				
Shipping weight (lbs)	157				
Shipping weight (kg)	71.1				
UPS housing material	Steel				
Cooling method	Fans				
ENVIRONMENTAL					
Operating Temperature Range	+32 to +104 degrees Fahrenheit / 0 to +40 degrees Celsius				
Storage Temperature Range	+5 to +122 degrees Fahrenheit / -15 to +50 degrees Celsius				

Relative Humidity	0 to 95%, non-condensing				
AC mode BTU / hr. (full load)	1767				
AC economy mode BTU / hr. (full load)	765				
Battery mode BTU / hr. (full load)	1784				
AC economy mode efficiency rating (100% load)	96%				
Operating Elevation (ft)	0-3000m (0 to 10,000 ft.)				
Audible Noise	60 dBA at front side 1 meter				
COMMUNICATIONS					
Communications interface	USB (HID enabled); DB9 Serial; EPO (emergency power off); Slot for SNMP/Web interface				
Network monitoring port description	Additional contact closure support with optional RELAYIOCARD and RELAYIOMINI interface cards. RELAYIOMINI installation requires removal of panel containing USB ports				
PowerAlert software	Included				
Communications cable	USB, DB9 serial and EPO cables included				
WatchDog compatibility	Yes				
LINE / BATTERY TRAN	SFER				
Transfer time	No transfer time (0 ms.) in online, double-conversion mode				
Transfer time (economy mode)	8 ms. typical power failure response in optional economy mode				
Low voltage transfer to battery power (setpoint)	156V (full load) / 100V (50% load or less, derates linearly)				
High voltage transfer to battery power (setpoint)	280V (full load) / 300V (90% load or less)				
SPECIAL FEATURES					
Cold Start (startup in battery mode during a power failure)	Cold-start operation supported				
High availability UPS features	Automatic inverter bypass; Manual bypass switch; Detachable hot-swap PDU; Hot swappable UPS power module; Hot swappable batteries				
Green & high efficiency features	High efficiency economy mode operation; Support for daily startup and shutoff; Schedulable daily hours of economy mode operation				
CERTIFICATIONS					
UPS Certifications	Tested to UL1778 (USA); Tested to CSA (Canada); Meets FCC Part 15 Category A (EMI); ROHS (Restriction of Hazardous Substances)				
UPS Certification details	IEC 61000-4-5 1995 B Surge Immunity				
	1				

Product Warranty Period (U.S., Canada & Puerto Rico)	2-year limited warranty	
Connected Equipment Insurance (U.S., Canada & Puerto Rico)	\$250,000 Ultimate Lifetime Insurance	

Related Items

Optional Products

Product Type	Related Model	Description	Qty.
Environmental Monitoring	ENVIROSENSE	Monitors temperature, humidity and contact-closure inputs. (Requires SNMPWEBCARD or switched PDU.)	1
Extended Warranties	WEXT3-SU6000HV	3-Year Extended Warranty - For SU6000RT3UHV only	1
Extended Warranties	WEXT5-SU6000HV	5-Year Extended Warranty - For SU6000RT3UHV only	1
External Battery Packs	BP192V12-3U	BP192V12-3U - External Battery Pack for UPS System	1
Rackmount/Wallmount Kits	2POSTRMKITHD	Enables 2-Post Rackmount Installation of 3U and Larger UPS, Transformer and Battery Pack Components	1
SNMP Accessories	RELAYIOCARD	Programmable Relay I/O Card	1
SNMP Accessories	SNMPWEBCARD	For remote monitoring and control via SNMP, Web, or Telnet.	1
Tower Stands	2-9USTAND	Enables Tower Placement of Rackmount UPS Systems	1
UPS Accessories	RELAYIOMINI	3 Relay I/O Mini-module	1

More information, including related products, owner's manuals, and additional technical specifications, can be found online at www.tripplite.com/en/products/model.cfm?txtModelID=4526.

Copyright © 2011 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.