

NOTES, UNLESS OTHERWISE SPECIFIED:

This tool is intended to be used to terminate Panduit OPTICAM connectors. The tool emits a laser beam, which, when used in conjunction with patch cord (sold separately), creates a glow effect from the connector which aides in proper connector termination.

Contact Panduit Corp. for a list of available replacement and additional parts for OPTICAM connector products.

This tool contains a Class IIIa/3R Laser and is manufactured to comply with: IEC/EN 60825-1:2001; and also with 21 CFR 1040.10 and 1040.11, except for those deviations pursuant to Laser Notice No.

Recommended use: With available patch cords only

Red laser diode 635nm Class IIIa/3R Laser

2 type AAA - 1.5 volt Alkaline batteries

Approx. 15 hours of continuous use

 0° C to 40° C

2.0" x 1-3/4" x 6-3/4" (51mm x 44mm x 171mm) All dimensions are for reference only.

4.7 oz (133 g) without batteries

F:/rvusers/engdocs/custdwg/FG24922B01	01 OCTT CD.doc
	_0.00.00.000

	NDUIT	COF	RP. TINLEY PARK, ILLINOIS	5	
OCTT* <i>OptiCam</i> Termination Tool					
Customer Drawing					
ILESS OTHERWISE SPECIFIED, IENSIONAL TOLERANCES ARE: ± (.xxx) ±) ± ANGLES ±		UNLESS OTHERWISE SPECIFIED, ALL DIMENSIONS ARE GIVEN IN INCHES, THIRD ANGLE PROJECTION.			
AWN BY: BLR	MATL:		SCALE		
те: 8-31-05			DRAWING NO.	DWG	
K'D: ABJ			FG24922B01	B SIZE	