

Standard features

- Expandable to 192 fully programmable hardwire and/or wireless zones
- 240 user codes
- Up to 192 addressable devices can be used
- 512-event history log that provides date, time, event and user number
- Up to 8 true partitions with separate account codes, entry/exit delays, and feature selections for each partition
- Maximum of 32 keypads with up to 8 per partition
- Wireless technology with up to 192 supervised zones
- 2-wire or 4-wire smoke detector compability
- Fire alarm verification for greater false alarm immunity
- Dynamic battery test
- Standard RS-232 on-board interface

Overview

The NetworX NX-8E is a full-featured security system that uses advanced technology for burglary, fire and environmental detection. The NX-8E is a flexible security system that is both easy to install and simple to use. With eight partitions and up to 192 zones, the NX-8E can handle your most demanding commercial and residential security needs.

Outstanding features

The NX-8E panel comes standard with eight hardwire zone inputs and two relays. Four programmable outputs can be set up to activate external devices during an alarm or other system event. The modular design allows for complete integration of multiple systems within one enclosure. Adding more zones or expanding capability is fast and easy.

Convenient and flexible

Conduct quick and easy on-site programming with alphanumeric keypads and a menu-driven text interface. Off-site programming is also available with the DL-900 software for Windows.

NetworX Control Panel NX-8E



NetworX Control Panel NX-8E

Specifications

- Operating Power – 16.5V AC 40VA
- Auxiliary w/40VA or 50VA transformer – 2 Amp
- Auxiliary w/NX-320E power supply – 3 Amps*

Loop resistance

- For standard loop – 300 Ω Maximum
- For 2-wire smokes – 30 Ω Maximum

Operating temperature

- 32° to 120°F

Dimensions

- 6.40 inches wide
- 4.0 inches high
- 1.10 inches deep

Shipping weight

- 9 pounds

* When using the NX-320E (w/50VA transformer) rated at 2 Amps and NX-8E (w/40VA or 50VA transformer) rated at 1 Amp, the combined available power is 3 Amps.

Available Keypad Styles



LED with
Removable Door



LCD with
Removable Door



Fixed Display with
Removable Door



LED with
Removable Door

Customer Service and Technical Support:
1-888-GE Security (437-3287)

12345 SW Leveton Drive
Tualatin, OR 97062
Phone: 503-692-4052
USA & Canada: 800-547-2556

www.gesecurity.com