

DIVAR IP 2000

www.boschsecurity.com



BOSCH
Invented for life



DIVAR IP 2000 is an affordable, easy to use all-in-one recording and management solution for network surveillance systems of up to 16 channels (all channels pre-licensed). Running the full Bosch recording solution including the Video Streaming Gateway to integrate 3rd party cameras, DIVAR IP 2000 is an intelligent IP storage device that provides both, a professional video recording solution and ease of operation.

DIVAR IP 2000 is a 4-bay mini tower unit that combines advanced management and state-of-the-art recording management into a single cost-effective, plug and play IP recording appliance for IT-minded customers which are seeking for a state-of-the-art “second generation” NVR recording solution.

System overview

DIVAR IP 2000 utilizes a highly energy efficient, embedded design at a very affordable price which nevertheless boasts Bosch quality through-and-through.

Easy to install and operate, the DIVAR IP 2000 system features wizard-based set-up and centralized configuration to reduce installation times by as much as 45%. All components are pre-installed and pre-



- ▶ Fully featured video recording solution for up to 16 channels
- ▶ Out-of-the-box IP video recording solution with up to 8 TB (4 x 2 TB) storage capacity
- ▶ Robust, secure operation – instant real time access to video
- ▶ Instantly find what you are looking for
- ▶ Remote viewing via Video Security App and Video Client by Bosch

configured. Simply connect to the network and power the unit up – DIVAR IP 2000 is ready to begin recording straight out-of-the-box.

Functions

DIVAR IP 2000 features front-swappable SATA-II hard drives providing up to 8 TB of gross storage capacity. All system software is pre-installed and pre-activated – creating an out-of-the-box ready-to-use video recording appliance. The DIVAR IP 2000 system utilizes Microsoft Windows Storage Server 2008 R2 (64-bit).

Remote viewing

DIVAR IP 2000 comes with our advanced Video Client for remote viewing. Video Client is a Windows PC application for live viewing and playback including Configuration Manager.

Configuration Manager allows the settings of DIVAR IP 2000 be configured.

A stand-alone archive player will allow archive playback and authentication without any other workstation software.

Instant real time access to video

View high quality HD video despite low or limited bandwidth connections. Dynamic Transcoding technology ensures you can view your video immediately – anytime, anywhere.

Dynamic Transcoding retrieves the data from DIVAR IP 2000 and subsequently decodes and decompresses the data stream to a lower rate bit stream tailored to the bandwidth of the connection. When the video is paused, the instant detail enhancement feature instantly displays the full HD video.

IP management and monitoring

Microsoft Windows Storage Server 2008 R2 provides a simple, intuitive user interface for system configuration and unified appliance management. Administrators and IT professionals will appreciate the ability to manage DIVAR IP 2000 using the built-in Microsoft System Center Suite compatibility. The ability to use one central tool for configuration and operations management reduces installation and training requirements, and helps keep ongoing system management costs low.

Bosch quality

Bosch subjects all its products to the most comprehensive and rigorous battery of quality endurance tests in the industry. Our recording products are subjected to extreme temperatures, voltages and vibrations to determine true operating limits, so you can be assured of long-term reliable operation. And Bosch firmly stands behind every product it sells with an end-to-end 3 year warranty backed by technical support.

Certifications and approvals

Region	Certification	
Europe	CE	DIVAR IP 2000/3000
USA	UL	DIVAR IP 2000/3000

Installation/configuration notes

DIVAR IP 2000 comes pre-configured in a standard non-RAID configuration and provides the following specifications:

Gross capacity	Net capacity	Bandwidth (read & write)	Cameras
w/o HDD	n/a	100 Mbit/s	16
2 x 2 TB	3600 GB	100 Mbit/s	16
4 x 2 TB	7300 GB	100 Mbit/s	16

These values refer to the Bosch recording applications; net capacity for a non-RAID configuration; 16 connected cameras indicate the number of concurrent recordable cameras including the connected replay clients.

DIVAR IP 2000 allows a maximum of overall 16 channels: recording and replay clients.



Notice

Bosch is not liable for system failures of units equipped with non-Bosch hard drives if the non-Bosch hard drives are source of the issues.

Parts included

Processor	
Processor	Intel Atom D525 processor + Intel ICH 9R storage controller
Socket	1
Chipset	Intel 82801IR I/O controller hub (ICH 9R) (Southbridge)
Memory	
Memory type	DDR3 SO-DIMM
Max front side bus	1333 MHz
Memory installed	4 GB, DDR3-1333 SO-DIMM (2 x 2 GB)
Storage	
Storage type	4 trays: 3.5-inch SATA
Hard drives installed	4 x HDD (2 TB 5400RPM GP) max
Graphics	Graphics memory controller integrated in the Intel Atom D525 processor
Network	1 x 1 GbE RJ45 port
System status	

DIVAR IP 2000 family comes fully loaded and fully functional with Microsoft Operating System and Bosch application pre-installed: Windows Server 2008 R2, 64-bit; Bosch Video Recording Manager including Video Streaming Gateway; Dynamic Transcoding.

Technical specifications

Electrical	
Power supply	220 W (100/240 VAC)
Energy efficiency	Energy Star compliant power supply
Power consumption (w/o hard drives)	37 W max 32 W idle
Mechanical	
Form factor	4-bay mini tower
Power supply	1 x internal power supply
USB ports	3 x USB 2.0, 2 x USB 3.0 port
Network	1 x Gigabit Ethernet LAN

Mechanical	
Dimensions (H x W x D)	180 x 200 x 212 mm (7.09 x 7.87 x 8.35 in)
Weight	w/o HDD: 4.25 kg (9.37 lb) fully loaded: 6.75 kg (14.88 lb)
Environmental	
Operating temperature	+10 °C to +35 °C (+50 °F to +95 °F)
Non-operating temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Operating relative humidity	8 to 90% (non-condensing)
Non-operating relative humidity	5 to 95% (non-condensing)

Additional information

Video clips for guided setup and configuration are available on the Security Systems Video Portal.
<http://video.boschsecurity.us/category/digital-recording/26>

Ordering information**DIVAR IP 2000, 2 HDD**

All-in-one recording and management solution for network surveillance systems of up to 16 channels, 2 x 2 TB storage capacity
 Order number **DIP-2042-2HD**

DIVAR IP 2000, 4 HDD

All-in-one recording and management solution for network surveillance systems of up to 16 channels, 4 x 2 TB storage capacity
 Order number **DIP-2042-4HD**

DIVAR IP 2000, w/o HDD

All-in-one recording and management solution for network surveillance systems of up to 16 channels, w/o HDD
 Order number **DIP-2040-00N**

Accessories**DIVAR IP HDD**

DIVAR IP 2000/3000 – 2000 GB HDD
 Order number **DIP-2302-HDD**

Represented by:**Americas:**

Bosch Security Systems, Inc.
 130 Perinton Parkway
 Fairport, New York, 14450, USA
 Phone: +1 800 289 0096
 Fax: +1 585 223 9180
security.sales@us.bosch.com
www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V.
 P.O. Box 80002
 5617 BA Eindhoven, The Netherlands
 Phone: + 31 40 2577 284
 Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
 11 Bishan Street 21
 Singapore 573943
 Phone: +65 6571 2808
 Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
 201 Building, No. 333 Fuquan Road
 North IBP
 Changning District, Shanghai
 200335 China
 Phone +86 21 22181111
 Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
 Via Anhanguera, Km 98
 CEP 13065-900
 Campinas, Sao Paulo, Brazil
 Phone: +55 19 2103 2860
 Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com