EMERGENCY PHONE ACCESSORIES



ETP-GSM Cellular Interface

Description

ETP-GSM Cellular Interface transforms any Talkaphone 100series or 400-series emergency phone into a wireless device where other communication interfaces are not available.

Features

- Supports the GSM, UMTS, and HSPA+ 3G network standards
- RJ11 port allows direct connection of 100-series or 400-series emergency phone
- · Rugged aluminum enclosure
- Includes dual-band 800/1900MHz omnidirectional antenna and 17' extension cord



Dimensions: 1.2(30.5) H x 4.3(109.2) W x 6.5(165.1) D in(mm)

Weight: 1.0 lbs. (0.45 kg)

Mounting: Designed to fit wireless towers and wall mounts

Operating Temperature: -40°F to 176°F (-40°C to +80°C) Humidity Range: 5% to 95%, non-condensing

Power: 6-16 VDC, 22 watts

Network Provider: AT&T

Cellular Connection: GSM, UMTS, HSPA+

LEDs: Power, status, cellular link, signal strength

Options

Upgrade from ETP-CI: Order model ETP-GSM-UPGRADE to upgrade from existing ETP-CI cellular interface

(does not include an antenna; includes an antenna adapter).

External power supply: Order model **86396** to add a 12VDC, 5A outdoor rated power supply.

IMPORTANT NOTE: Programming of the ETP-400 Series Phones cannot be done through a remote call to the ETP-GSM Cellular Interface. An ETP-400 Series Phone must be programmed over a standard analog phone line connection.

IMPORTANT NOTE: The built-in auto-dialer of the ETP-400 Series Phone cannot dial a secondary number in round robin fashion when used in conjunction with the ETP-GSM Cellular Interface.

IMPORTANT NOTE: All programming, diagnostics, and identification of Talk-A-Phone analog emergency phones are accomplished through the transmitting and receiving of DTMF signals. Cellular transmissions may interfere with and distort these tones. As a result of these irregularities, model ETP-TAL Talk-A-Lert diagnostic and base station package may not function as intended and, therefore, may not be appropriate in that application or environment.

In any event, programming of the Talk-A-Phone analog emergency phone should be done on a land line.

