

Speed Dome Keyboard Controller

KBDPTZ1

Features

- · Capable of controlling up to 32 speed domes
- 2 levels of passwords (administrator and user) are supported for higher security
- Programmed data from up to 2 domes can be downloaded to non-volatile memory space and uploaded to a new dome
- Control a camera's panning and tilting movement with variable speeds from 0.5'/sec. to 90'/sec., as well as its zoom, focus and iris command
- Normal speed is inversely proportional to the current zoom ratio
- Turbo speed is max. 380'/sec. when "Ctrl" key is pressed
- Define and recall up to 240 presets, which are immediate camera call-ups of preset position view with automatic zoom and focus
- Able to define and run up to 8 patterns comprising of a sequential series of pan, tilt, zoom and focus movements from a single camera
- Define and run up to 8 scans which scan between 2 limits
- Incorporate up to 300 presets, patterns, scans and 8 tours
- Presets, patterns and scan are automatically displayed one after the other on the main monitor
- Programmable user preferences (alarm, preset, title, etc.)



Specifications

 Power Consumption
 .12VDC, 0.5W

 Control Method
 .RS-485

 Baud Rates
 .RS-485 2400 - 230K bps

 Dimensions
 .15" (W) x 6.5" (L) x 2.75" (H)

 Weight
 .2.5 lbs

 Power Supply
 .12VDC@1.5A

 (power supply included)

Controls the Following Dome Cameras:

HTSD10X HT65010XS OPTZ36XO HTSD37X HT650PT10X OPTZ36XI

Speco Technologies is constantly developing and improving products. We reserve the right to modify product design and specifications without notice and without incurring any obligation.

Rev. 2/28/12