

# M12 Rugged Distribution Boxes, One Signal Per Socket, On-Board M23 Connection, with or without LED

### ASBS-R 4 5-4 | ASBS-R 8 5-4

ASBS-R 4/LED 5-4 | ASBS-R 8/LED 5-4







### 4- and 8-Ports

ASBS-R pluggable actuator/sensor distributor, 4 or 8 x M12 ports, 4-poles, with LED operating and function display, one signal per socket, ground connection, M23 connection for the control cable, 12-poles

### 4-Ports



### 8-Ports



## Pin Assignments

M12	Wiring Diagrams	
4-Ports		8-Ports
3 0 0 1 = 2 = 3 = 3 = 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0	10 n.c. (-) 10 12 (-) 12 (-) 13 (-) 13 (-) 14 (4)	1 = 11 (+) 2 = n.c. 3 = 9 (-) 10 4 4 1 (1) 4 = 1 (1) 2 (2) 3 (3) 4 (4) 5 (5) 6 (6) 7 (7) 8 (8) 5 = 12 (PE)

## Be Certain with Belden



# M12 Rugged Distribution Boxes, One Signal Per Socket, On-Board M23 Connection, with or without LED

### **Technical Data**

#### **Environmental Conditions**

Degree of protection IP65 / IP67

Pollution severity 3

Operating temperature range -40°C / +80°C (dragchain and UL max. 60°C)

Materials

Contact CuZn, pre-nickeled and gold-plated

Contact bearer TPU-GF
Housing Zinc die casting

O-ring FKM

**Electrical Data** 

Rated voltage 30 V

Rated current\* 4 A per outlet / 12 A max. total; at 40°C

 $\begin{array}{ll} \mbox{Rated impulse voltage} & 32 \mbox{ V} \\ \mbox{Contact resistance} & \leq 5 \mbox{m} \Omega \\ \mbox{Insulation resistance} & > 10^9 \ \Omega \\ \end{array}$ 

### **Additional Technical Data**

operation display: LED Green Function display / channel status:

LED Channel A: Yellow

Part Number		Ports	Characteristics
ASBS-R 4 5-4	ASBS-R 4/LED 5-4	4	
ASBS-R 8 5-4	ASBS-R 8/LED 5-4	8	

<sup>\*</sup> only in locked position with its proper counterparts or dust covers