

3-Breaker Parallel Tie Cabinet (for SU80K 3-Phase UPS)

MODEL NUMBER: SUPT80K



Highlights

- 3 breaker parallel tie cabinet accessory for two Tripp Lite 3 phase UPS systems
- Enables dual-UPS redundancy or links the output of two UPS systems for double-capacity
- 3 built-in circuit breakers, heavy duty copper buswork
- Compatible Tripp Lite SU80K 3 phase UPS systems

Description

Tripp Lite's parallel tie cabinet provides a means for safely paralleling two UPS systems for either redundancy or additional capacity. Redundant configuration provides fault-tolerance to maintain network operations during failure of one UPS. Non-redundant configuration combines the output of two UPS systems to support twice the output current. Two input breakers receive incoming pwoer from the UPS and are connected to heavy duty copper buswork and an output breaker rated for the total UPS capacity of the two UPS systems combined. See downloads section for <u>Tripp Lite 3-Breaker Parallel Tie Cabinet</u> detailed specifications, dimensional drawings, operational flow charts and technical description of each included component.

Compatible with two Tripp Lite SU80K UPS systems.

Specifications

OVERVIEW	
Model Type	Tie Cabinets
Accessories Type	Parallel Tie Cabinet
INPUT	
Nominal Input Voltage(s) Supported	208V AC
Voltage Compatibility (VAC)	208
PHYSICAL	
Shipping Dimensions (hwd / in.)	46.85 x 38.85 x 12.55
Shipping Dimensions (hwd / cm)	119 x 98.7 x 31.9



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Unit Dimensions (hwd / in.)	46.1 x 38.1 x 11.8
Unit Dimensions (hwd / cm) Unit Weight (lbs.)	117.1 x 96.8 x 30
Unit Weight (kg)	143
Form Factors Supported	Wallmount
WARRANTY	

© 2015 Tripp Lite. All rights reserved. All trademarks are the sole property of their respective owners. Tripp Lite has a policy of continuous improvement. Specifications are subject to change without notice. Photos may differ slightly from final products.