

## Overview


The American Power Conversion<sup>®</sup> Metered Rack PDU distributes power to devices in the rack. It has a sensor that measures the current that it and its attached devices use. It can be monitored through Web, Telnet, SNMP, SSH, or InfraStruXure<sup>™</sup> Manager interfaces.

**Outlets.** The Rack PDU has twenty-one (21) NEMA 5-20 outlets and six (6) NEMA L6-20 outlets.

**Display interface.** A digital display shows aggregate current being used by the Rack PDU.

**Power cord.** The 3-foot (0.91-meter) power cord terminates with a NEMA L21-20 connector.

## AP7863





## Specifications for AP7863

## Electrical

Input connector	NEMA L21-20 plug
Output connectors	(21) NEMA 5-20 outlets, (6 )NEMA L6-20 outlets
Nominal input voltage	120/208 VAC 3-phase
Acceptable input voltage	$\pm$ 10% of normal voltage
Input frequency	47–63 Hz
Physical	
$(\mathbf{H} \times \mathbf{W} \times \mathbf{D})$	70.00×2.19×1.73 in (177.80×5.56×4.39 cm)
Shipping dimensions $(H \times W \times D)$	84.00×6.00×5.00 in (213.36×15.24×12.7 cm)
Weight	12 lb (5.4 kg)
Shipping weight	19.5 lb (8.8 kg)
Environmental	
Maximum elevation (above MSL) Operating Storage	15 000 ft (4500 m) 50 000 ft (15 000 m)
Temperature Operating Storage	–5 to 45° C (23 to 115° F) –25 to 65° C (–13 to 149° F)
Humidity Operating Storage	5–95% RH Non-condensing 5–95% RH Non-condensing
Compliance	
EMC verification	FCC Part 15 Class A ICES-003 Class A
Safety verification	UL, cUL 60950



990-1952

07/2004