APC External Battery Pack

Extended battery backup time for the Back-UPS Pro 1500 VA models

The BR24BPG is an external battery pack that plugs into the rear panel of 1500VA Back-UPS Pro models. Connecting the BR24BP battery pack will approximately triple the normal amount of runtime provided by your standard Back-UPS Pro unit.





Product Features:

- Four 9Ah batteries dramatically extend the runtime of your 1500VA Back-UPS Pro unit. (1500VA Back-UPS Pro models contain two 9Ah batteries standard.)
- Consistent styling with APC's Back-UPS Pro models.
- Recharges automatically via the Back-UPS Pro's internal charger.
- Heavy duty connector plugs securely into the rear panel of the 1500VA Back-UPS Pro.
- Vented, high strength, flame retardant housing provides durability and efficient thermal management.
- 2 year warranty



Rear of BR1500G (sold separately)



BR24BPG Specifications				
Model Number	BR24BPG			
Output				
Output Voltage	12Vdc			
Output Connection	proprietary, non-reversible connector			
Input				
Input Voltage	12Vdc			
Physical				
Unit Dimensions (H x W x D)	11.9 x 4.4 x 15.0" (30.1 x 11.2 x 38.2 cm)			
Unit Weight	29.5 lbs (13.4 kg)			
Shipping Dimensions (H x W x D)	15.0 x 9.0 x 19.0" (381 x 229 x 483 cm)			
Shipping Weight	32.1 lbs (14.6 kg)			
Color	Black			
UPC Code	731304268789			
Compatibility				
The BR24GBP and BR24BP are interchangeable, but their styling and color are significantly different.	Use BR24GBP with: BR1500G (NAM), BR1500-AR (Argentina), BR1500G-BR (Brazil), BR1500G-CN (China), BR1500G-FR (France), BR1500G-GR (Germany), BR1500G-IN (India), BR1500GI (Worldwide)			
	Use BR24BP with: BR1500, BX1500 (NAM), BR1500I (Worldwide)			
Battery				
Expected Life	4 - 6 yrs			
Battery Type	Maintenance-free, sealed lead-acid battery, leakproof			

Approx Runtimes: 1500VA Back-UPS Pro with and without the BR24BPG External Battery Pack

LOAD: <u>Watts</u> /			untime with e BR24BPG
50 /	80 157	min 4	46 min
100 / 1	60 80	min 2	32 min
200 / 3	20 37	min 1	10 min
300 / 4	80 22	min	69 min
400 / 6	40 14	min	49 min
500 / 8	10 10	min	37 min
600 / 9	60 7 1	min	29 min
700 / 11	20 5	min	24 min
800 / 13	33 4	min	20 min

For more information on runtimes, go to: www.apc.com/sizing

APC by Schneider Electric 132 Fairgrounds Rd West Kingston, RI 02892 Tel: 800-800-4272 www.apc.com

