## **LOUDSPEAKER ASSEMBLIES**



# FM4X1/70

## **FOREGROUND MUSIC**

2-Way - 4" O.D. LF Speaker & 3/4" HF,
70V Rotary Select Transformer with 8Ω Tap, Black Finish

#### **GENERAL DESCRIPTION**

The **FM4X1/70** is complete 2-way loudspeaker with a 4" O.D. Woofer, 3/4" dome tweeter, 20W-70V low loss, extended frequency response rotary select transformer with an 8 Ohm position in a black finish. Multiple position "U" braket included.

# **INTENDED USE - Indoor Environment**

Program Material | Signal tones, voice, and music | Installation | Horizontal or Vertical Surface Mount

## **AUDIO SPECIFICATIONS**

Average Sensitivity
Loudspeaker Power Rating
8 Ohm Tap Output
Calculated Output
Frequency Response
Nominal Coverage Angle

89 dB SPL, 1W/ 1M 20W RMS, EIA 426A Standard 89 dB SPL, 1W/ 1M 102 dB SPL, 5W/ 1M 80Hz - 20kHz EIA 426A Standard

80Hz - 20kHz EIA 426A Standard 90° Included Angle, -6 dB / 2 kHz, half space


Audio Connection | Binding Screw


# **SYSTEM COMPONENTS**

Loudspeaker Tweeter Transformer 4" O.D. Woofer 3/4" Dome Integral to Unit

20W-70V or 8 Ohm, 5 tap (20W, 10W, 5W, 2.5W, 1.25W)







Recommended construction sequences, installation instructions, and A&E Specifications are available in various formats in the QUAM Architects' and Engineers' Resources section on the web at: www.QuamSpeakers.com



