LOUDSPEAKER ASSEMBLIES

CEILING MOUNT

Includes TWO (2) Each: C10X/BU/WS, ERD8U, SSB-3

GENERAL DESCRIPTION

The **SOLUTION 1** is a complete speaker/transformer/baffle solution for ceiling installations. Each installer package includes two (2) C10X/BU/WS -The 8C10PAX - 8" O.D. dual cone loudspeaker with a 10 oz. magnet and a TBLU - 5W-25/70V transformer mounted on a BR8WS - round, steel, stud mount baffle. Also included are two (2) SSB-3 - rust-resistant steel, load bearing supports and two (2) ERD8U - 275 CID, round, steel back boxes.

* SHIPPED AS A COMPLETE PAIR IN ONE CARTON

INTENDED USE - Indoor Environment

Program Material | Signal tones, voice, and music **Installation** Downward-Firing in a 24" Wide, Drop-Tile Ceiling


AUDIO SPECIFICATIONS

Average Sensitivity **Loudspeaker Power Rating Calculated Output** Magnet Type & Weight Frequency Response **Nominal Coverage Angle** Audio Connection

95 dB SPL, 1W/1M 20W RMS, EIA 426A Standard 102dB SPL, 5W/ 1M BeFe Ceramic, 10 oz. Nominal 60Hz - 17 kHz EIA 426A Standard 90° Included Angle, -6 dB / 2 kHz, Half space


7" Color Coded Leads





C10X/BU/WS





41/4

SYSTEM COMPONENTS


8C10PAX Loudspeaker

5W-25/70V: 5 tap, Color Coded Leads Transformer


(5W, 2.5W, 1.25W, 0.63W, 0.31W)

Baffle BR8WS **Back Box** ERD8U Mounting Device SSB-3





Recommended construction sequences, installation instructions, and A&E Specifications are available in various formats in the OUAM Architects' and Engineers' Resources section on the web at: www.QuamSpeakers.com









QUAM-NICHOLS COMPANY, INC. 234 East Marquette Rd. Chicago, IL. 60637 Tel: 1-800-NEED-NOW (800-633-3669) Fax: 1-888-NEED-NOW (888-633-3669) e-mail: NeedNow@QNC.com www.QuamSpeakers.com