ADAM-4541 ADAM-4542+ ADAM-4561/4562

Multi-mode Fiber Optic to RS-232/422/485

Single-mode Fiber Optic to RS-232/422/485

1-port Isolated USB to RS-232/422/485 Converter







Specifications

General

 Power Input Unregulated 10 ~ 30 V_{DC} Connectors

1 x plug-in terminal block (#14 ~ 22 AWG) (RS-232/422/485) 2 x ST fiber connector

■ Power Consumption 1.5 W @ 24 V_{DC}

Serial Communications

 Communication Mode

Asynchronous

Speed Modes (bps)

9,600, 19.2 k, 38.4 k, 57.6 k. 115.2 k and RS-232/422 mode (switchable)

1,200, 2,400, 4,800,

Full/half duplex, Transmission Mode

bidirectional

Fiber Optic Communications

Optical Power Budget 12.5 dB (measured with 62.5/125 µm) (Attenuation)

Transmission Distance

Wavelength

2.5 km

Transmission Mode Multi mode

(Send and Receive)

820 nm

ADAM-4542+

USTED US ROHS CEFCC

Specifications

Specifications

General

 Power Input Unregulated 10 ~ 30 V_{DC} Connectors 1 x plug-in terminal block

(#14 ~ 22 AWG) (RS-232/422/485) 1 x SC fiber connector

Power Consumption 3 W @ 24 V_{DC}

Serial Communications

 Communication Mode

 Speed Modes (bps) 1,200, 2,400, 4,800,

9,600, 19.2 k, 38.4 k, 57.6 k. 115.2 k and RS-232/422 mode (switchable)

Asynchronous

• Transmission Modes Full/half duplex, bidirectional

Fiber Optic Communications

Optical Power Budget 15 dB (Attenuation)

Transmission

15 km

Distance

Transmission Mode Single mode

(Send and Receive)

Wavelength 1310 nm

Connectors

General

Network: USB-type A connector (type A to type B

cable provided) Serial:

1 x plug-in terminal ADAM-4561

(#14 ~ 22 AWG) (3-wire RS-232/422/485) 1 x DB-9 serial connectors

(9-wire RS-232)

Isolation Voltage

ADAM-4562

ADAM-4561 3,000 V_{DC} $2,\!500\;V_{\text{DC}}$ ADAM-4562:

Power Consumption

ADAM-4561: 1.5 W @ 5 V ADAM-4562: 1.1 W @ 5 V Driver Support Windows 98/2000/XP

Full Compliance with USB v1.1 specifications

Serial Communications

• Speed Modes (bps) 75 bps to 115.2 kbps • Transmission Modes Full/half duplex,

bidirectional

Common Specifications

Environment

Humidity 5 ~ 95% RH

 Operating ADAM-4541/4542+: -10 ~ 70° C (14 ~ 158° F) ADAM-4561/4562: 0 ~ 70° C (32 ~ 158° F) Temperature

 Storage Temperature -25 ~ 85°C (-13 ~ 185°F)

Ordering Information

ADAM-4541

Multi-mode Fiber to RS-232/422/485

Converter

ADAM-4542+

Single-mode Fiber to RS-232/422/485

Converter

ADAM-4561

1-port Isolated USB to RS-232/422/485 Converter

1-port Isolated USB to

ADAM-4562

RS-232 Converter