









# 8000 SERIES HYBRID NVRs AT-A-GLANCE

	32 CHANNELS			16 CHANNELS		8 CHANNELS		4 CHANNELS
								
<b>Model Number</b>	8732 R	8532 R	8532 S	8516 R	8516 S	8708 S	8508 S	8704 S
<b>Base Part Number</b>	28065	28066	28067	28646	28068	28570	28568	28569
<b>Total Inputs</b>	32	32	32	16	16	8	8	4
<b>Analog/IP Inputs</b>	16/32	16/32	16/32	16/16	16/16	8/8	8/8	4/4
<b>IP Licenses Included</b>	32	32	32	16	16	8	8	4
<b>Analog Performance</b>	480 FPS @ 4CIF	240 FPS @ 4CIF	240 FPS @ 4CIF	240 FPS @ 4CIF	240 FPS @ 4CIF	240 FPS @ 4CIF	120 FPS @ 4CIF	120 FPS @ 4CIF
<b>IP Performance</b>	96 Mbps	96 Mbps	96 Mbps	48 Mbps	48 Mbps	24 Mbps	24 Mbps	12 Mbps
<b>IP Performance with Alternate Stream</b>	72 Mbps	72 Mbps	72 Mbps	32 Mbps	32 Mbps	18 Mbps	18 Mbps	9 Mbps
<b>Analog Compression</b>	H.264			H.264		H.264		H.264
<b>Local Area Network</b>	GigE			GigE		GigE		GigE
<b>Camera Network</b>	GigE			GigE		GigE		GigE
<b>Analog Resolutions</b>	4CIF/2CIF/CIF			4CIF/2CIF/CIF		4CIF/2CIF/CIF		4CIF/2CIF/CIF
<b>IP Resolution</b>	Camera dependent, up to 10MP			Camera dependent, up to 10MP		Camera dependent, up to 10MP		Camera dependent, up to 10MP
<b>Operating System</b>	Embedded Linux			Embedded Linux		Embedded Linux		Embedded Linux
<b>Alarms</b>	8 In / 4 Out			8 In / 4 Out		2 In / 1 Out		2 In / 1 Out
<b>Audio</b>	4 In / 2 Out			4 In / 2 Out		2 In / 1 Out		2 In / 1 Out
<b>Local Control</b>	Yes (IP Camera Capable)			Yes (IP Camera Capable)		Yes (IP Camera Capable)		No
<b>Composite Out</b>	Yes (IP Camera Capable)			Yes (IP Camera Capable)		Yes (IP Camera Capable)		No
<b>Max HDDs</b>	4			4		2		2
<b>Max HD Storage</b>	Up to 24 TB			Up to 24 TB		Up to 12 TB		Up to 2 TB
<b>Storage Redundancy</b>	Mirroring (reduces throughput)			Mirroring (reduces throughput)		Mirroring (reduces throughput)		Mirroring (reduces throughput)
<b>Data Ports</b>	4 USB, 1 RS-232, 1 RS-485			4 USB, 1 RS-232, 1 RS-485		4 USB, 1 RS-232		2 USB, 1 RS-232
<b>Docking Station</b>	Yes	Yes	No	Yes	No	No	No	No
<b>Dimensions (H x W x D)</b>	3.1 x 17.4 x 16.0 in (8.0 x 44.2 x 40.6 cm)	3.1 x 17.4 x 16.0 in (8.0 x 44.2 x 40.6 cm)	3.2 x 16.9 x 16.0 in (8.1 x 43.0 x 40.6 cm)	3.1 x 17.4 x 16.0 in (8.0 x 44.2 x 40.6 cm)	3.2 x 16.9 x 16.0 in (8.1 x 43.0 x 40.6 cm)	3.6 x 11.3 x 12.0 in (9.18 x 28.7 x 30.6cm)	3.6 x 11.3 x 12.0 in (9.18 x 28.7 x 30.6cm)	3.2 x 8.3 x 5.0 in (8.1 x 21.2 x 12.6 cm)
<b>Environmental</b>	41° to 105° F (5° to 40° C)			41° to 105° F (5° to 40° C)		41° to 105° F (5° to 40° C)		41° to 105° F (5° to 40° C)
<b>Power Supply</b>	Internal 115/230 VAC (auto-sensing); 75 W max			Internal 115/230 VAC (auto-sensing); 75 W max		External 110/220 VAC (auto-sensing); 60 W max		External 110/220 VAC (auto-sensing); 20 W max
<b>Weight</b>	18.5 lbs (8.4 Kg)	18.5 lbs (8.4 Kg)	13 lbs (5.9 Kg)	18.5 lbs (8.4 Kg)	13 lbs (5.9 Kg)	7.3 lbs (3.3 Kg)		3.3 lbs (1.5 Kg)
<b>Battery Backup</b>	Yes			Yes		Yes		Yes
<b>Mounting Options</b>	Dock, Desk, Wall	Dock, Desk, Wall	Desk, Wall	Dock, Desk, Wall	Desk, Wall	Desk, Wall	Desk, Wall	Desk, Wall
<b>Front Panel QR Code*</b>	Yes			Yes		Yes		Yes
<b>Analytics</b>	Included: Motion Detection    Optional: Camera Detection, Field of View Monitoring, Trip Wire, Loitering, Presence Detection							

\*The QR Code on the front panel contains useful information about the recorder, such as model number and serial number. When the code is scanned using the March Networks GURU smartphone application, this information allows integrators to easily check warranty status, initiate an express RMA, get in-field diagnostics support, review and change recorder IP addresses, register/unregister from the Enterprise Service Manager, and go through SSH to view storage information — saving them time and money.

North America . . . . . 1 800 563 5564  
 Latin America . . . . . +5255 5259 9511  
 Europe . . . . . +39 0362 17935  
 Asia . . . . . +65 6818 0963  
 Australia and New Zealand . . . . . +61 1300 089 419  
 Middle East and Africa . . . . . +971 4 399 5525

© 2014, March Networks, An Infinova Company. All rights reserved. Information in this document is subject to change without notice. MARCH NETWORKS, March Networks Command, March Networks Searchlight, March Networks RideSafe, Shadow Archive and the MARCH NETWORKS logo are trademarks of March Networks Corporation. Infinova is a trademark of Infinova Corporation. All other trademarks are the property of their respective owners. 060-3172-01-E [marchnetworks.com](http://marchnetworks.com)

### 2-year Advance Replacement plan on all NVRs:

- Options for Repair & Return or Advance Replacement
- March Networks incurs all shipping costs—both ways—for AR's
- All NVR components are covered, including HDDs