Illuminated RTE Plates with Square Buttons

SD-7202GC-PEQ *Stainless-steel plate*
SD-7202GC-PTQ *Stainless-steel plate with timer*
SD-7223GW-LQ *Plastic white plate*

Features:

- Large illuminated pushbutton with caption "PUSH TO EXIT"
- Message language can be easily switched between English, Spanish, and French with 3 included interchangeable plates:

- Pushbutton rated 10A@125~250VAC (3A@24VDC for **SD-7202GC-PTQ**)
- Includes five colored 12-inch wire leads with easy-to-attach spade lugs for fast installation
- LED gives over 50,000 hours of illumination
- 12~24 VDC: No resistors required
- Includes stainless-steel single-gang plate
SD-7223GW-LQ only:
- White plastic single-gang plate
SD-7202GC-PTQ only:
- Timed output adjustable from 1~180 seconds
- Buzzer output for audible status

SD-7202GC-PEQ
SD-7202GC-PTQ

**SD-7223GW-LQ**

Wiring:

Pushbutton

Green wires (light)
(12VDC ~ 24VDC)

White wire (COM)
Max. 10A@125~250 VAC

Blue/white wire (N.O.)
(Top Lug)

Green/white wire (N.C.)
(Bottom Lug)

Timer (SD-7202GC-PTQ only)

Timer Adjustment Trimpot

(–) (+)
(N.C.) } Buzzer Output
(N.O.)
(COM) } Relay Output
(COM)
(N.C.)
(N.O.) } Trigger Input (Factory prewired)

Power Input 12~24 VAC or VDC (non-polarized)

SECO-LARM® U.S.A., Inc.

16842 Millikan Avenue, Irvine, CA 92606
Phone: (949) 261-2999 | (800) 662-0800 **Fax:** (949) 261-7326
Website: www.seco-larm.com **Email:** sales@seco-larm.com

SECO-LARM® **ENFORCER**® **CRIMEBUSTER**® CBA *SLI*

Pi_SD-7202GC-PxQ_080415.docx