



18v X2 LXT® Lithium-Ion (36v) Cordless Blower Kit (5.0Ah)

Model XBU01PT

Kit Includes LXT® Blower, Dual Port Charger and 2 ea. 18v LXT® 5.0Ah Batteries



POWER

Makita-built motor produces a maximum air velocity of 208 MPH



SPEED

2-speed (Low: 10,000 RPM, High: 17,000 RPM) design to match the speed to application



INNOVATION

Two 18V LXT® Lithium-Ion batteries deliver the power and run time for corded demands



CONVENIENCE

Zero emissions and reduced maintenance for increased ease of use



Uses **2**
18v LXT®
Batteries

5.0Ah
BATTERY

LXT® X2 18V 18V 36V

FEATURES

- Makita-built Motor Produces a Maximum Air Volume of 155 CFM
- Compact and ergonomic design at only 36-1/4" long
- Weighs only 8 lbs. with batteries for reduced operator fatigue
- Rubberized soft grip provides increased comfort on the job
- Instant start-up; simply load two 18V LXT® batteries and the blower is ready to use
- 18V LXT® Lithium-Ion 5.0Ah battery BL1850B features an integrated L.E.D. battery charge level indicator
- 18V LXT® Lithium-Ion 5.0Ah battery BL1850B provides up to 65% more run time per charge compared to 3.0Ah battery BL1830
- 18V LXT® Lithium-Ion 5.0Ah battery BL1850B reaches a full charge in 45 minutes or less

SPECIFICATIONS

Max. Air Volume	155 CFM
Max. Air Velocity	208 MPH
No Load Speed (2 spd)	10,000/17,000 RPM
Battery	2X 18V LXT® Lithium-Ion
Sound Pressure	86 dB(A)
Overall Length	36-1/4"
Net Weight (with battery)	8 lbs.
Shipping Weight	13.1 lbs.
UPC Code	088381-847520

STANDARD EQUIPMENT

- (2) 18V LXT® Lithium-Ion 5.0Ah Batteries (BL1850B)
- 18V LXT® Lithium-Ion Dual Port Charger (DC18RD)

OPTIONAL ACCESSORIES

- 18V LXT® Lithium-Ion 3.0Ah Battery (BL1830B)
- 18V LXT® Lithium-Ion 4.0Ah Battery (BL1840B)
- 18V LXT® Lithium-Ion Rapid Optimum Charger (DC18RC)
- 18V LXT® Lithium-Ion 4-Port Charger (DC18SF)