

Our most innovative kit yet!



ARLP-UL-M-KIT

- PTS “PUSH TO SET” TECHNOLOGY
- COMMAND ACCESS DESIGNED CUSTOM MOTOR --NO CLEARANCE ISSUES
- FULL PUSH PAD RETRACTION --BALL SCREW INTEGRATION FOR INCREASED TORQUE
- WORKS ON 88/86/84/82 SERIES
- PATENT PENDING

The new **ARLP-UL-M-KIT** is a robust, ground breaking field installable motorized latch retraction kit for Adams Rite 8000 series exit devices. It utilizes a custom ball screw assembly and CAT designed custom stepper motor to maximize the pulling force in a package small enough to fit inside all Adams Rite 8000 devices with no clearance issues.. The only hole you’ll need to drill is the raceway! It utilizes our **PTS** “Push to Set” technology making post installation adjustments incredibly easy. Watch the video! You’re gonna love it!

SPECIFICATIONS

VOLTAGE:

- Voltage range - 22 to 28 VDC
- System protection - unit shutdown when voltage exceeds 28VDC
- Average Current Peak - 1.3A
- Average Current Hold -170mA
- PTS adjustment - approx. 1/4”

WIRE RUN:

- 500’ with 18ga wire
- 700’ with 16ga wire

PRODUCT DETAILS:

- Box: 10.5” x 3.75”: x 2.5”
- Weight: 2 Lbs
- 15 Master Pack:
- Weight: 30 ILbs 12.75” x 11.75” x 11”

RECOMMENDED LOCKING HARDWARE POWER SUPPLIES:

- | | |
|----------------|----------|
| ● PS204/PS204B | ● PS480B |
| ● PS210 | ● PS1 |
| ● PS220/220B | ● PS2 |
| ● PS440B | ● PS5-8 |

FEATURES:

- MM4 Smart Module: On board diagnostics with audible feedback for adjustment and power issues
- “PTS”: 5 second electronic adjustment for easy post installation adjustment
- Electric dogging rated for continuous duty - Auto engage if dogged push pad is pulled from position
- Low current draw
- Field switchable to a “High Torque” mode
- Up to 500’ wire run with 2-18ga wire - Long wire runs provides installer with convenience of placing the locking device power supply in a centralized location; i.e. the same closet as the access panel
- 8’ cable with Quick Connect for MM4 module to easily connect to power supply lead
- 3-year “no hassle” warranty

ACCESSORIES:

- Request to Exit (REX) - Available as a field installable kit

U.S. Customer Support
1-888-622-2377

Visit our website for more details
www.CommandAccess.com

Canada Customer Support
1-855-823-3002



HOW TO ORDER

Part #	Easy Order #	Description
ARLP-UL-M-KIT	76736	Kit for the Adams Rite 8000 series. EU 24 VDC.
ARREXKIT-M-ED	79013	Field installable REX kit for Adams Rite 8000 series.

CUTDOWN DETAILS:

- 36" Model - Max Cut 0"
- 42" Model - Max Cut 5.5"
- 48" Model - Max Cut 4"

ARLP-UL-M-KIT MATRIX

The ARLP-UL-M-KIT will work in new installations and as a replacement for installations with existing electrifications, matrix lists available options.

Adams Rite Kit	Mechanical unmodified	CAT Modified Solenoid	CAT Modified Motor	AR Solenoid	AR Motor (SE)	SDC Motor
ARLP-UL-M-KIT	8000 ✓	✓	✓	✓	-	✓
ARREXKIT-M-ED	✓	-	✓	✓	✓	✓

Check out the installation video



[Scan or click](#)