

Door Openers

Mortise

9 Series

The 9E and 9G mortise door openers are long service devices, providing the security and convenience of remote control door-lock operation. These units are flush mounted in place of the regular door strike plate. The door remains locked until the opener is electrically actuated by a contact device. For AC operation, use with an 88-50 or 598 Transformer.

- #### Features and Specifications
- Fits left and right hand doors
 - Easy installation
 - Rugged, heavy duty construction
 - For use in wood jambs



Ordering Information					
Description	Cat. No.	Operating Voltage	Current	Transformer Cat. No.	Finish
Mortise Door Opener	9E	4 - 6V DC	1.3 - 2.7 A	—	Brushed aluminum and lacquered faceplate and nosing
		8 - 16V AC	1.3 - 2.7 A	12V tap of 88-50 or 598	
	9G5	24V AC	1.4 A	598	Brushed aluminum and lacquered faceplate and nosing

Weights and Dimensions	
Cat. No.	Approx. Shipping Weight (lb.)
9E	0.80
9G5	0.80

