

# MultiCharger14-2.4A Overview



## Key Features

- Charging up to 2.4A per port

The MultiCharger14-2.4A has been designed primarily for desktop use, with the option to wall mount. Being highly compact and quiet the reliable lightweight device is excellent for charging your USB devices. The MultiCharger14-2.4A offers 2.4A of charging to each port making it ideal for charging within your workplace, school, hospital, and many more.

The MultiCharger14-2.4A is a smart USB hub which is used to connect and charge multiple USB devices such as Mobile phones, Tablets and any other device with a USB connection. There are 14 downstream ports on the MultiCharger14-2.4A which will allow you to charge and connect to multiple devices at the same time.

The MultiCharger14-2.4A provides 12W of charging power to each of its 14 Type-A ports, allowing mobile devices to be charged quickly, safely and reliably.

More information can be found by visiting our website and downloading the product user manual.

[www.cambrionix.com/product-user-manuals](http://www.cambrionix.com/product-user-manuals)

Physical Specifications	
Downstream connector type	Type-A
Dimensions WxDxH (mm)	199x73x42
Weight (kg)	1.5
Number of downstream ports	14

Power Specifications	
Input Voltage (V)	12
Input Current, Max (A)	15
Input Connector	4-Pin Mini-DIN
Output Current, Max per Port (A)	2.4
Output Power, Max per Port (W)	12
Output Power, Total (W)	174.72
Output Voltage, (V)	5

What's Included
<div>MultiCharger14-2.4A</div> <div>2m Mains power cable</div> <div>Power Supply Unit</div>

Part Number	Description
MC14-2.4A-UK-G	MultiCharger14-2.4A with UK type-G Power cable
MC14-2.4A-US-B	MultiCharger14-2.4A with US type-B Power cable
MC14-2.4A-EU-F	MultiCharger14-2.4A with EU type-F Power cable
MC14-2.4A-IND-D	MultiCharger14-2.4A with Indian type -D Power cable
MC14-2.4A-JP-B	MultiCharger14-2.4A with Japanese type-B Power cable
MC14-2.4A-AU-I	MultiCharger14-2.4A with Australian type-I Power cable

